



Banner Multicharger 4x5A

Fully automatic charger for 12 V batteries with 4 stations

Latest, microprocessor controlled charging technology guarantees optimum battery charging, maximum safety and easy handling.

The LED display shows the status of charge at each individual charging station.

Ideal for recharging of stored batteries in stocks or workshops and for safe maintaining several batteries over many months.



FEATURES

Battery Voltage: for 12 V batteries

Charging Function: fully automatic, 5-step charging, automatic switchover to conservation charging

Display: multicolor LED-Display for each station

Construction: robust housing, isolated quality clamps

Safety Features: protection against reverse polarity, over-voltage and short-circuit

Mounting: suitable for desk or wall mounting

Contents: charger, 4 x clamps and instruction manual

APPLICATION

Shop, Stock, Workshop

12 V Batteries



TECHNICAL DATA

Type:	Mutlicharger 4x5A
Input Voltage:	220-240 VAC, 50/60 Hz
Battery Voltage:	12 V
Charging Voltage:	up to 14.7 V
Charging Currant:	max. 5 A per station
Protection:	IP20
Protection:	35 x 19 x 7.5 cm
Charging Cable:	180 cm
Weight:	2.5 kg
Ambient Temperature:	-0 °C bis +50 °C

ITEM NUMBER

1240004500